

Modular Sensor Interface MSI 60



- ▶ 50 sensor inputs (differential analogue, single ended analogue, LVDT, frequency, RS232)
- ▶ High quality signal processing
- ▶ Compact dimensions

The MSI 60 is a high quality signal conditioning and data acquisition unit for analogue, digital, frequency and linear variable differential (LVDT) sensors.

MSI 60 offers a large number of freely configurable inputs (32 x differential analogue, 8 x single ended analogue, 8 x LVDT, 2 x frequency, 1 x RS 232 for GPS). Possible applications of the differential inputs include e.g. 31 TC-J type or TC-K type temperature sensors arranged in a sensor array (one diff. input used for compensation), PT100, PT1000 (specific pull up values available), NTC, strain gauges etc. Each differential input features 200 times oversampling.

The cut-off frequency of the digital filters in all inputs is automatically adjusted to match the acquisition rate. MSI 60 also corrects the latency of the digital filters during recording, yielding zero filter delay in the recorded data. Quantization of each MSI measurement channel is individually configurable. Data can be sent via Ethernet interface to any Bosch Motorsport logging device.

Technical Specifications

Mechanical Data

Size	153 x 119 x 38 mm
Weight	645 g
Aluminum housing	
High density type motorsport connectors	
Vibration damped printed circuit boards	
Operating temperature	-20 to 85°C
Max. vibration	15 g sinus at 1,200 Hz for t < 5 h

Electrical Data

Max. power consumption (w/o sensor power supply)	15 W
Required power supply	7 to 18 V
2 frequency inputs 0 to 25.5 kHz for inductive sensor / Hall-effect sensor / DF11 sensor	
32 differential analogue inputs, switchable to single ended operation, -5 V to 5 V or 0 V to 5 V; switchable pull up values 3.01 kOhm and 4.99 kOhm, 49.9 kOhm to suit PT100/PT1000	
8 single ended analogue inputs, 0 V to 5 V; switchable pull up value 3.01 kOhm	
8 LVDT inputs, 2.5 kHz/5 kHz/10 kHz; 3 V/5 V/10 V RMS	
4 PWM outputs, max. 1 A each, max. 1 kHz	
2 x 5 V or 10 V switchable sensor power supply, max. 200 mA each	
2 x 5 V sensor power supply, max. 400 mA each	
1 x sensor power supply, max. 800 mA voltage = (MSI 60 supply voltage) -1.1 V; switched U_Batt	
RS 232 interface for GPS (data reception only)	
3 x Ethernet 100 MBit/s	
2 x freely configurable up to 1 MBit CAN Bus	

Environment

Software Upgrade 1

CCP-Master (ASAP 2 file from ECU manufacturer required)	F 02U V01 012-01
---	------------------

Connectors and Wires

Connector LIVE (red)	AS212-35PN
Mating Connector	AS612-35SN; max. AWG22 F 02U 000 443-01

Connector SENSOR 1 (yellow)	ASDD214-64PA
Mating Connector	ASDD614-64SA; max. AWG24 F 02U 003 098-01
Connector SENSOR 2 (red)	ASDD214-64PN
Mating Connector	ASDD614-64SN; max. AWG24 F 02U 000 854-01

Ordering Information

Modular Sensor Interface MSI 60

Order number **F 02U V01 901-01**

Software Options

SW Upgrade 1

Order number **F 02U V01 012-01**

Represented by:

Europe:

Bosch Engineering GmbH
Motorsport
Robert-Bosch-Allee 1
74232 Abstatt
Germany
Tel.: +49 7062 911 9101
Fax: +49 7062 911 79104
motorsport@bosch.com
www.bosch-motorsport.de

North America:

Bosch Engineering North America
Motorsport
38000 Hills Tech Drive
Farmington Hills, MI 48331-3417
United States of America
Tel.: +1 248 876 2977
Fax: +1 248 876 7373
motorsport@bosch.com
www.bosch-motorsport.com

Asia-Pacific:

Bosch Engineering Japan K.K.
Motorsport
18F Queen's Tower C, 2-3-5 Minato
Mirai Nishi-ku, Yokohama-shi
Kanagawa 220-6218
Japan
Tel.: +81 45 650 5610
Fax: +81 45 650 5611
www.bosch-motorsport.jp

Australia, New Zealand and South

Africa:
Robert Bosch Pty. Ltd
Motorsport
1555 Centre Road
Clayton, Victoria, 3168
Australia
Tel.: +61 (3) 9541 3901
motor.sport@au.bosch.com